

INSTALLATION INSTRUCTIONS

600 Series

Slip the leads through the universal crossbar and aluminum ring, attach to the socket.

Align the socket keyhole openings through the crossbar slots to the 3.5" c-c tapped holes on the junction box. Attach with the 8-32 screws.

The crossbar will accommodate different J box types as well. Different sized screws may be required.

Note the aluminum ring can be rotated to orient the brass thumbturns.

Attach the threaded rods to the 6.125" c-c holes as far as the stop nuts. Small holes may be needed in the ceiling or wall to accommodate the back side of the rods.

For the No. 623 fixture, use the 5.75" c-c holes.

Slip the fixture over the rods and secure with the brass thumbturns. Do not overtighten.

SPECIFICATIONS

Junction box: octagonal metal or round plastic, attachment holes 3.5" c-c, 8-32 tapped. Other J box types are possible.

Socket: E26

Maximum wattage: 60W, 110-240 volts

Base diameter: 6.625"

Projection: 2" without bulb

Weight of all components: 2 lbs

To be installed by a licensed electrician.

